

PRODUCT INFORMATION SHEET

| | |
|---------------------|------------------------------|
| Model No | SRK-RT103-2T |
| Brand | SIRKOM |
| Product type | Android Tablet |
| Product Description | 10.1" L-Type Digital Signage |

INSHOP Digital

www.inshopdigital.com
sales@inshopdigital.com



| | | |
|--------------------|------------------|--|
| System | CPU | RK3288 Quad core cortex A17 |
| | RAM | 2GB |
| | Internal memory | 16GB |
| | Operation system | Android 8.1 |
| | Touch screen | 10-Point capacitive touch |
| Display | Panel | 10.1"LCD |
| | Resolution | 1280*800 |
| | Display mode | Normally black |
| | Viewing angle | 85/85/85/85 (L/R/U/D) |
| | Contrast ratio | 800 |
| | Luminance | 250cd/m2 |
| | Aspect Ratio | 16:10 |
| Network | WiFi | 802.11b/g/n |
| | Ethernet | 10M/100M/1000M |
| | Buletooth | Bluetooth 4.0 |
| Interface | Card slot | TF,support up to 32GB |
| | USB | USB for serial (RS232 format) |
| | USB | USB host 2.0 |
| | Type-c | USB OTG Onely |
| | Power jack | DC power input |
| | Earphone | 3.5mm earphone output |
| | RJ45 | Ethernet interface |
| Media play | Video format | MPEG-1,MPEG-2,MPEG-4,H.265,H.264,VC-1,VP8, etc.,support up to 4K |
| | Audio format | MP3/WMA/AAC etc. |
| | Photo | jpeg |
| Other | NFC | Optional ,NFC 13.56MHz, ISO14443A/ISO14443B/ISO 15693/Mifare classic/Sony felica |
| | Microphone | Dual microphone |
| | Speaker | 2*2W |
| | Camera | 5.0M/P_front camera |
| | Language | Multi-language |
| | Working temp | 0--40degree |
| Accessories | Certificates | |
| | Adapter | Adapter, 12V/1.5A |
| | User manual | yes |

Product Measurement, mm

| Unit (Without packaging) | | | Giftbox (With Packaging) | | | Carton 6pcs/CTN | | |
|--------------------------|---|---|--------------------------|---|---|-----------------|---|---|
| L | W | H | L | W | H | L | W | H |
| | | | | | | | | |
| Net(kg) | | | Net(kg) | | | Net | | |
| | | | | | | G.W | | |

Drawing

